

## HANTEK USB Oscilloscope



<b>HANTEK 6022BE</b>	
<b>Channel</b>	2
<b>bandwidth</b>	20MHZ
<b>Single bandwidth</b>	DC to 20 MHZ
<b>Real-time sampling rate-Max</b>	48MS/s
<b>Storage depth</b>	1M
<b>Vertical resolution</b>	8Bit
<b>impedance</b>	1MΩ 25pF
<b>Coupling</b>	DC
<b>Voltage range</b>	20mV-5V, 8Steps
<b>Vertical Accuracy</b>	±3%
<b>range</b>	1ns-5000s, 39 Steps
<b>The vertical position can be adjusted</b>	Yes
<b>Input protection</b>	Diode
<b>X-Y</b>	yes
<b>Horizontal</b>	Automatic, standard, single
<b>trigger slope</b>	+/-
<b>Trigger level can be adjusted</b>	Yes
<b>TRIGGER SOURCE</b>	CH1,CH2
<b>Pre-trigger</b>	0-100%
<b>Sampling rate choice</b>	Yes
<b>Fai line shows</b>	HP/line, brightness to adjust
<b>network</b>	on/off
<b>Cursor measurement</b>	yes
<b>arithmetic</b>	Fast Fourier transform, reverse, add, subtract, multiply and divide.
<b>Cursor shows</b>	Frequency and voltage
<b>Accessories</b>	S/W CD, probes, manual, USB cord